


DS-PK1-E-WE Wireless Keypad

The DS-PK1-E-WE series wireless keypad can connect to AX PRO for alarm control and operation. It can also notice alarm by indicator and buzzer.



Features

- 868 MHz two-way wireless communication
- AES-128 encryption
- Stay/away arming, disarming, alarm clearing for specified area or all areas
- LED indicates the programmed area
- One-Push fire alarm, panic alarm, and medical alarm. Silent/Audible alarm selectable. etc.
- Output control
- Full touch key design with LED backlight
- Fully remote configurable through App
- Multiple enrollment methods and easy installation design
- Easy replaceable battery
- Frequency hopping against jamming for reliable transmission

Available Models

DS-PK1-E-WE



Specifications

Model		DS-PK1-E-WE
RF	Frequency	868 MHz
	Modulation	2GFSK
	Distance	1200m (open area)
Interface & component	Tamper switch	Supported, front and rear panel tamper-proof
	Power switch	Power on/off
	Buzzer	Supported
	Indicator	4: fault (orange), enrollment/signal (red/green), arm(blue), disarm(green) and alarm (red)
	Backlight	white
	Key	Number key: 0 to 9 Function key: *, #, stay arming, away arming, disarming, and output
Application & protocol	Protocol	Tri-X, two-way communication
Electrical & battery	Power Consumption	Quiescent current: 180 uA Max current: 251mA Voltage: 1.5 VDC
	Battery type	Four AA batteries
	Battery life span	Standby time more than two years
Others	Operation humidity	10% to 90% (No condensing)
	Operation temperature	-10 °C to +55 °C (-4 °F to +122 °F)
	Color	White
	Installation	Screw mounting
	Dimension (W x H x D)	140 (5.50") x 86 (3.38") x 22 (0.87") mm
	Weight	Without batteries: 151 g (5.33 oz), and 23 g (0.81 oz)each battery

Distributed by



HIKVISION®

Headquarters

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8807-5998
overseasbusiness@hikvision.com

Hikvision USA
T +1-909-895-0400
sales.usa@hikvision.com

Hikvision Australia
T +61-2-8599-4233
salesau@hikvision.com

Hikvision India
T +91-22-28469900
sales@pramahikvision.com

Hikvision Canada
T +1-866-200-6690
sales.canada@hikvision.com

Hikvision Thailand
T +662-275-9949
sales.thailand@hikvision.com

Hikvision Europe
T +31-23-5542770
sales.eu@hikvision.com

Hikvision Italy
T +39-0438-6902
info.it@hikvision.com

Hikvision Brazil
T +55 11 3318-0050
Latam.support@hikvision.com

Hikvision Turkey
T +90 (216)521 7070- 7074
sales.tr@hikvision.com

Hikvision Malaysia
T +601-7652-2413
sales.my@hikvision.com

Hikvision UK & Ireland
T +01628-902140
sales.uk@hikvision.com

Hikvision South Africa
Tel: +27 (10) 0351172
sale.africa@hikvision.com

Hikvision France
T +33(0)1-85-330-450
info.fr@hikvision.com

Hikvision Kazakhstan
T +7-727-9730667
nikia.panfilov@hikvision.ru

Hikvision Vietnam
T +84-974270888
sales.vt@hikvision.com

Hikvision UAE
T +971-4-4432090
salesme@hikvision.com

Hikvision Singapore
T +65-6684-4718
sg@hikvision.com

Hikvision Spain
T +34-91-737-16-55
info.es@hikvision.com

Hikvision Tashkent
T +99-87-1238-9438
uzb@hikvision.ru

Hikvision Hong Kong
T +852-2151-1761
info.hk@hikvision.com

Hikvision Russia
T +7-495-669-67-99
saleru@hikvision.com

Hikvision Korea
T +82-(0)31-731-8817
sales.korea@hikvision.com

Hikvision Poland
T +48-22-460-01-50
info.pl@hikvision.com

Hikvision Indonesia
T +62-21-2933759
Sales.Indonesia@hikvision.com

Hikvision Colombia
sales.colombia@hikvision.com